

**NCB211 - 2 CHANNELS NIM FAN OUT 1-8**

The NIM module NCB211 has 2 independent channels NIM FAN OUT 1 to 8 signals. Each channel has two output LEMO connectors that can be terminated to  $50\ \Omega$ .

**PERFORMANCE**

Input	50Ω
Output	16mA negative NIM pulse
Rise/fall time	< 2 ns
Input/output delay	< 6 ns
Input frequency	130 MHz

**POWER SUPPLY REQUIREMENTS**

The module has NIM standard power supply.

P. Voltage (V)	Current/ch (mA)
-6	400

**DIMENSIONS**

dimensions	3,43x22,13 cm per DOE/ER-0457T
weight	1 kg